

INSTALLATION DATA

230 -240 VOLT				
KVA RATING	FUSE SIZE	WIRE SIZE B & S	REQUIRED AMPS	DISCONNECT SIZE
5	20	8	16	30
10	40	6	32	60
15	60	4	48	60
20	80	2	64	100
30	125	2/O	96	100
40	175	3/O	128	200
50	200	4/O	160	200
75	300	400 MCM	242	400
100	400	500 MCM	320	400
125	500	(2) 300 MCM	400	600
150	600	(2) 400 MCM	482	600
200	800	(2) 500 MCM	640	1200
250	1000	(2) 600 MCM	800	1200
300	1200	(3) 500 MCM	964	1200
460 - 480 VOLT				
KVA RATING	FUSE SIZE	WIRE SIZE B & S	REQUIRED AMPS	DISCONNECT SIZE
5	10	10	8	15
10	20	8	16	30
15	30	8	24	30
20	40	6	32	50
30	60	4	48	50
40	80	2	64	100
50	100	0	80	100
75	150	3/O	121	200
100	200	4/O	160	200
125	250	300 MCM	200	400
150	300	400 MCM	241	400
200	400	500 MCM	320	600
250	500	600 MCM	400	600
300	600	750 MCM	482	600